

Error: Device driver software was not successfully installed -or- Your printer failed to install. (Windows XP - Any Printer)

Error: Device driver software was not successfully installed -or- Your printer failed to install. (Windows XP - Any Printer)

1. Power on the printer using the power button. This forces the PC to re-recognize the device. (If starting at this step, simply connect USB and power to the printer.)

2. Within a few moments, a found new hardware wizard will appear on your screen. (If it does not appear, unplug both the power and USB from the printer, wait a few seconds and plug them back in.)

3. Choose "No, not this time" when asked to search the web for a driver. (Depending on which XP service pack you have this message may or may not appear.)



4. Choose "Install from a list or a specific location", click next and continue with step 12.

Found New Hardware Wizard		
	If Driver has been Downloaded from our Website. This wizard helps you install software for:	
	Disc Publisher II If your hardware came with an installation CD or floppy disk, insert it now.	
	What do you want the wizard to do?	
	 Install the software automatically (Recommended) Install from a list or specific location (Advanced) 	
	Click Next to continue.	
	< Back Next > Cancel	

5. Choose "Don't Search, I will choose the driver to install". Click Next.

Found New Hardware Wizard		
Please choose your search and installation options.		
Search for the best driver in these locations.		
Use the check boxes below to limit or expand the default search, which includes local paths and removable media. The best driver found will be installed.		
Search removable media (floppy, CD-ROM)		
Include this location in the search:		
C:\BravollDriver Browse		
On't search. I will choose the driver to install.		
Choose this option to select the device driver from a list. Windows does not guarantee that the driver you choose will be the best match for your hardware.		
< Back Next > Cancel		

6. If prompted for hardware type, choose "Printer". Click Next. (This screen usually does not appear.)

Found New Hardware Wizard				
Hardware Type.				
Select a hardware type, and then click Next. Common hardware types:				
 Ports (COM & LPT) Printers Processors SBP2 IEEE 1394 Devices SCSI and RAID controllers Secure Digital host controllers Smart card readers Sound, video and game controllers Storage volume shadow copies 				
< Back Next > Cancel				

7. Click the "Have Disk" button to browse to the driver location. (Do not pick a driver from the Manufacturer - Printers list.)

Found New Hardware Wizard				
Add Printer Wizard				
Select the manufacturer and model of your printer. If your printer came with an installation disk, click Have Disk. If your printer is not listed, consult your printer documentation for a compatible printer.				
Manufacturer	Printers AGFA-AccuSet v52.3 AGFA-AccuSetSF v52.3 AGFA-AccuSet 800 AGFA-AccuSet 800SF v52.3			
This driver is digitally signed. <u>Tell me why driver signing is important</u>				
	< Back Next > Cancel			

8. Click the Browse button.

Install From Disk				
5	Insert the manufacturer's installation disk, and then make sure that the correct drive is selected below.	OK Cancel		
	Copy manufacturer's files from:	Browse		

9. Browse to the file. If you downloaded the driver from the website and ran the extractor program, the files will be located in a folder at the root of your C-Drive. The folder and file will be named for the specific printer you will be installing. In this example you will be browsing for C:\Documents and Settings\
<Username>\Local Settings\Temp\Setup\PostSetup. Once the file has been located, click Open.



10. Verify the location and click OK.



Found New Hardware Wizard			
Add Printer Wizard			
Select the manufacturer and model of you disk, click Have Disk. If your printer is no compatible printer.	ur printer. If your printer came with an installation t listed, consult your printer documentation for a		
Printers			
Disc Publisher II			
This driver is not digitally signed! Have Disk Have Disk			
	< Back Next > Cancel		

12. You will be prompted that the driver is not digitally signed or doesn't pass Windows Logo Testing. Click **Continue Anyway**.

Found New Hardware Wizard					
	Please wait while the wizard installs the software				
	File Progre	Hardware Installation			
		1	The software you are installing for this hardware: Printers has not passed Windows Logo testing to verify its compatibility with Windows XP. (Tell me why this testing is important.) Continuing your installation of this software may impair or destabilize the correct operation of your system either immediately or in the future. Microsoft strongly recommends that you stop this installation now and contact the hardware vendor for software that has passed Windows Logo testing.		
			Continue Anyway STOP Installation		

13. Files will be copied to the correct location.



14. Click Finish to complete the installation.



Related Articles:

Windows Vista Installation Instructions

Windows 7/Windows 8 Installation Instructions

Macintosh Installation Instructions

Article ID: 44613